



**Technical Data**

Function	read/write
Keyboard	32 keys alphanumeric
Display	LCD-Display, 20 characters / 4 Rows
Power Supply	2,4V Accupac NiMH
Capacity	1500mA/h
Interface	RS232/Balluff Dialog
Operating temperature	0...50°C
Protection per IEC 60529	IP 40
Read head connection	1x chinch 6,3mm
Description	Handy-Programmer
Accessories	Charger/Power Supply please order separately
Comments	The Handy programmer is a Service- and Testunit to validate and edit the content of a codetag. A read/write head will be connected A build-in RS232 Interface enables the data transfer with a PC. Customer specific menues are possible.  Please add the language sign D (for german) or E (for english) to the ordering code.